



## KVASER MEMORATOR PRO 5xHS CB

EAN: 73-30130-00832-8

Kvaser Memorator Pro 5xHS CB is a five channel, high performance, CAN bus interface and standalone datalogger that allows users to monitor and collect data from up to five CAN channels using just one device. It is supplied “bare board” i.e. without a housing, and can thus be built into any system. The Memorator Pro 5xHS CB supports CAN FD.

Configurable using Kvaser’s Memorator Config Tool, Memorator Pro 5xHS CB is capable of running user-developed scripts, written in the Kvaser t programming language. Guidance in creating t programs is supplied. The device is also supported in CANlib, Kvaser’s universal software development kit.

### Warranty

2-year warranty. See our General Conditions and Policies for details.

### Support

Free support for all products by contacting [info@gmga.vn](mailto:info@gmga.vn).

## Major Features

- Monitor 5 CAN channels simultaneously using just one device.
- Automatically time synchronises the data transmitted and received across all five channels.
- Built-in Kvaser MagiSync™ technology time synchronises with other Kvaser interfaces connected to the same PC, resulting in simpler and more accurate multichannel data capture.
- Script functionality allows users to develop customised t-script applications written in the Kvaser t programming language.
- Plug and play installation.
- Log data to an expandable SD card slot.
- Power derived from the USB connection, CAN bus, or an in-built power supply.

## Technical Data

<b>Bit Rate</b>	40 - 1000 kbps
<b>CAN Channels</b>	5
<b>CAN FD</b>	Yes
<b>Certifications</b>	CE, RoHS
<b>Connector</b>	Molex 51021 PicoBlade™
<b>Current Consumption</b>	Up to 3W
<b>Dimensions</b>	57 x 120 x 13 mm
<b>Error Frame Detection</b>	Yes
<b>Galvanic Isolation</b>	Yes
<b>Operating Temperature Range</b>	-40 °C to +85 °C
<b>PC Interface</b>	USB
<b>Silent Mode</b>	Yes
<b>Timestamp Resolution</b>	1 µs
<b><i>t-Script Support</i></b>	Yes
<b>Weight</b>	50g
<b>Operating Systems</b>	Windows, Linux

## Software

Documentation, Kvaser CANlib SDK and drivers can be downloaded for free, please free to contact us. Kvaser CANlib SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, Visual Basic, Python and t programming language.

Kvaser CAN hardware is built around the same common software API. Applications developed using one device type will run without modification on other device types